BOOX Nova

SMART READING SERIES

User Manual

Table of Contents

2. Standard Accessories	4
3. Safety Guide	5
4. Product Views	7
5. Main Interface	10
6. Library	16

1. About ONYX......2

7. Reading	24
8. Shop	51
9. Note	59
10. Storage	69
11. Apps	70
12. Settings	84
13. FAQ	94
14. Specifications	95
15. Declaration	96
(Note: The E-books in the following illustration are not pre direction)	-stored, just for

1. About ONYX

BOOX is presented by Onyx International, which has a group of professionals



who dedicate themselves in designing state-of-the-art reading terminal. The beauty of the BOOX is embodied in both its simplicity and its power. As we are going to show you, BOOX is an open and flexible platform for both consumers and content providers.

BOOX is powered by a 16-level grayscale e-ink screen that looks and feels like paper. Passive lighting and diffuse surface relax your eyes and reduce eye strain. By the hand-writing system, you can take notes while reading and sketch up ideas that happen to emerge. BOOX takes full advantage of new-generation e-ink screens: extremely low power consumption without reflection and backlight. Each full charge can sustain a few weeks' reading. By reducing paper consumption while providing a realistic paper-like reading experience, digital content helps to protect the environment without sacrificing convenience or lifestyle.

For content partners, we also provide support for custom formats and digital rights management solutions. All of our viewers have standard features such as layout management, font adjustment, full-text-search, zooming, and page flow.

Copyright © 2019 Onyx International. All rights reserved.



For a next-generation information device, connectivity is essential. The user can connect to the Internet by built-in Wi-Fi, 3G module or other add-on modules to download new content or surf the web. Customized for the e-ink screen, WebKit, the same software engine as some powerful desktop browsers such as Safari and Chrome, is the web browser of BOOX.

BOOX gives you a new reading experience.



2. Standard Accessories

(1) BOOX Note	Peader	v1
(I) BOOK NOIE	Reader	ΧI

Optional Accessories (Purchased separately)

(1) Adapter

(2) Protective case

*Stylus for Nova Pro, handwriting supported.

No stylus for Nova, handwriting unsupported.

The following * means it is only for Nova Pro.

3. Safety Guide

Please read the Safety Guide carefully before you start to use the device.

Contact your BOOX retailer if you have any technical problem, or you can dial our official service line at 4008-400-014 or 4008-860-830.

Copyright © 2019 Onyx International. All rights reserved.





Screen protection

The device is equipped with E-ink screen, which is very fragile. Please have no shocking, squeezing, pressing against the screen, or dropping the device from a higher place. If the screen is already broken, stop using it and contact the professional or other qualified staff to replace the screen for you. Please don't dismantle the device without our permission.



Standard accessories

Only the battery, adapter, and other accessories meeting our standard safety rules can be used for the device. For details, please refer to Product Specification. We will not be responsible for any damage caused by incompatible accessories.



Stay away from liquids



The device is not waterproof. Don't expose the device to a humid environment or use it in the rain. Please keep it away from any corrosive liquids.



Don't dismantle the device

Please don't dismantle the device in case of any damage.




Using environment

The using environment of the device is 0°C-50°C.



4. Product Views

Front View











Back View





Bottom View



Button Function

Power/	●Press the power button to turn on the device
Standby Button	●Press the power button and hold for 2-3 seconds to turn
	off the device. Or select "Power off" in the menu to turn



	off the device.					
	●Press the power button and release quickly to let the					
	device go standby or wake up.					
	●Exit the current apps;					
	●Exit the current view or dialog;					
Back Button	●Go back to the previous directory;					
	●Long press for 3 seconds to turn on/off front light for					
	those models with front lights.					
	●Blue LED indicator lights up when to power on					
Power Light	●In the state of charging or PC connecting, orange LED					
	indicator lights up					



5. Main Interface

TI	:	:		4 _ 4	I	content are		£ 4:	
ınΔ	main	Intertace	COntaine	a ctatile	nar	CONTANT 212	a ann	THINCTION	arga
1110	HIIAIII	IIIICHACC	COLITION	a status	vai.	CONTENT AIC	a. and	IUIICUOII	arca.

The function area contains certain modules.

Double click the icons in	function	area	can	return	to	the	main	page	of	the
specified module.							— Sta	tus ba	ar	

Content Area





(1) Status bar



This section displays the current state of the device, including Home, Battery



Status, Notification, Time, Front Light on/off, Hand Touch on/off, A2 Mode on/off, Multi-tasking switching.

Home

Go back to the homepage of the Library directly.

Two-grey level refreshment mode is good for a fast refreshment of text pages. It enables fast pageturn, no screen flashing and less ghosting background. When A2 mode is on, reading articles with images, graphics, texts mixed are not recommended because the images may not be fully shown.



A2 Mode is on



A2 Mode is off





In third-party apps, this indicated button is set as pageturn function by default for the pre-installed application of the device.



Front Light

Call out a panel to adjust front light luminance.



Hand Touch

For palm rejection, hand touch can be turned off (except for the status bar). The default hand touch is on after reboot.



Clicking this icon, pop up the Android multi-task list to check the running



applications in the background, one key to clear up all the applications to speed up the device.

Notification Interface

Click the middle of the Status Bar, the notification interface can be callout.

Notification interface contains battery percentage, WIFI setting,

Bluetooth setting, power saving mode, volume adjustment, ongoing

operation indication, etc.





Battery Status

It shows the current state of the battery including remaining capacity, use hour, the curve of the battery percentage.



WIFI Setting

When using at the first time, you should enter into the Wi-Fi setting interface to get a possible connection. Then click the icon to turn on/off the automatical connection.

Bluetooth Setting

When using at the first time, you should enter into the Bluetooth setting interface to match a device you want. Then click the icon to turn on/off the automatical Bluetooth connection.

Power Saving Mode

Prohibit third-party software from running in the background. Help to save power of the device.

Copyright © 2019 Onyx International. All rights reserved.

Volume Adjustment

Adjust the volume of a loudspeaker or bluetooth earphone, only for the devices without volume buttons.

(2) Function Area

The function area includes Library, Shop, Storage, Apps, and Settings.

(3) Content Area

The contents are sort by time by default. The contents are:

Library

All books in supported format from internal storage are displayed here. The scanning path can be modified at Settings - Library Settings.

Storage



All folders from internal storage will be displayed here. Users can manage documents and folders from the page.

Apps

All the third-party apps are displayed here. Users are allowed to manage or optimize the apps.

Settings

The list of system settings helps to manage the device.

6. Library

The library only displays E-book documents in supported formats in the storage.



Book cover thumbnail is displayed by default. E-books are sorted by the creation time.

Tapping the toolbar icon on the top right of the library, users can Search, Create sub-library, Multi-select, Filter & Sort by, and Rebuild Library.






Library Display Switch

Click on these icons to switch the library display. By default, it automatically scans and loads all the supported documents in the specified path, sorted by a specified way.

Another one is to display the content based on the structure of storage. The icons change after clicking on.




25 / 136



Filter & Sort







Refresh Library

"Refresh Library" get all documents in supported formats scanned and rebuild library list. This function does not delete the reading history.








Create Sub-library

It helps to manage books by file manager.





Sub-library Attribute

Long press against sub-library cover to view more information about sub-library.

To delete or rename sub-library are allowed. When deleting sub-library, the containing books will be moved to Library and will not be deleted with the sub-library.





E-book Attribute


Long press against book cover to view more information about E-book name, author, format, size, reading progress, book detail(only available for the E-

Copyright © 2019 Onyx International. All rights reserved.



books of Shop), open way, rename, move(to sub-library) and delete. One E-book only can be added to one Sub-library.

As for the books purchased from the Shop, is allowed to view book details by jumping to the Shop page.




7. Reading



Tap any E-book cover to open an E-book. Full-screen reading without showing status bar is set by default.

To tap on the center of the screen can call out the status bar and menu.



Word Menu

Long press on the word to pop up Dictionary dialog for lookups.


English word recognition and look-ups are supported.

Through the drop-down list on the top right of the dialog, the dictionary can be switched to others.

Users can download and install the dictionary themselves. Put dictionary file on the path root directory\dicts\xxx (e.g Storage\dicts\English-French), or download dictionary online directly. Dictionary is available to use after being installed.



Tap on any position out of the dialog to exit the dialog.




Long press on any word and drag to select the text you want to mark.

The highlight is set by default for selected text. Users can switch among highlight, underline and others, the color highlight can be in black or grey. The mark setting remains after a change. The marks before the change will not be affected.



Tap on any position out of the dialog to exit the dialog.



Choose "Annotation" to pop out a text box to add notes if needed.

The status bar includes multiple document tags (4 tags at most), top menu bar



and bottom menu bar.

Top Menu Bar

It contains: Back, Quick Writing (for some certain formats), Buy (for E-books of Shop), Front Light, TTS, Search, Refresh, and Settings.

S Buy

Only available for the books from the Shop. It jumps to the book detail page to purchase.

Quick Handwriting

For the scribble supported document, the stylus for handwriting is allowed by default. The function can be turned off, then the stylus is used for touch only.

ெ TTS

English supported. Network connection is required at first use.

C Refresh

The refresh modes are Normal Refresh (Regal Mode) and Fast Fresh (A2 Mode). Full refresh every specified page can also be set here.

Settings

These reading settings contain Global Settings, Touch Settings, TTS Settings, Export Settings, and Version.

Bottom Menu Bar (for PDF)

Doc, Progress, Format, Navigation Mode, and Scribble are included.

Doc

Doc contains TOC, Bookmark, Annotation, and Scribble.

TOC supports three-layer hierarchy. The current layer is underlined. Jump to the corresponding page when tapping any of the layers.

Tap on any position out of the TOC to exit.



Bookmarks

Without calling out the menu, bookmark the reading page by simply tapping a tag on the top right corner of the screen. Tap it again to un-bookmark the page.

The bookmarks can be checked under the path of Doc-Bookmark, where users can delete bookmarks.



Jump to the corresponding page by tapping any of the bookmarks.

Annotation

All highlighted/underlined/annotated content would be listed under the page of Doc-Notes for further searching, editing and deleting.

Jump to the corresponding page/content by tapping any of the lists.

All contents on the Annotation page can be exported in txt format. Exported files are saved under the directory folder Storage\Note\(same name as the source file).

Scribble

All scribble and sidenote can be viewed under the page of Doc-scribble for further searching and deleting.

Jump to the corresponding page by tapping any of the pages.

All scribble contents can be exported in Png format and saved under the same




directory folder Storage\Note\(same name as the source file).

Progress




It displays the chapter name (book name if no chapter), page progress, last/next chapter, page number, slideshow, undo, and redo.



Tap on the page number to enter a quick-flip interface. It can be flipped by every 1, 4, 9 pages.

Click the page numbers again and input number to jump to the page directly.





Format

Display, Contrast, and Reflow are included. This module is just available for the E-books in the formats of PDF\DJVU\CBR\CBZ.

Copyright © 2019 Onyx International. All rights reserved.

Display

It contains Layout, Orientation, Zoom, Crop, and Margin.

Layout: Single page, double pages (only in landscape mode).

Orientation: allowed to switch to four different orientations, the word orientation is the same as the orientation of "T".

Zoom: Zoom in, zoom out, and partial zoom are supported. Users can also pinch fingers together or apart to zoom out or in on the reading pages.

When zooming in until the whole page larger than the screen display, users can long press and drag to adjust the display area. Single click on the screen to turn the sub-page. Click on the virtual buttons on the bottom right to turn the whole page.



己,并可随时记录灵感。BOOX 充分利用了新

反光, 无背光, 给读者真实的阅读感, 极大降

同时符合人们长期以来的阅读习惯。

BOOX 支持格式定制和数字版管理方案。对

BY 10 BY 10 B

以及页面重排。

平台,网络互联功能非常重要。 BOOX 的用户:

All rights reserved. 04:17 PM










Contrast

Watermark, Sharpen, Image Contrast, Text Contrast, and Bold are included.

Some of the functions are just available for scanned documents.






Reflow

Reflow is only available for PDF/DJVU/CBR/CBZ documents.



Reflow allows users to further customize the layout of documents including: Line Spacing, Margin, Text Direction, Font Size, Columns, and Upright (for italic documents).






Navigation

Navigation allows users to have options of Reset, Comic Mode, Article Mode, and More Settings including Crop, Split, and Subpage Order.

Comic Mode: the screen will be divided into four subpages and the reading order is upper right – upper left – bottom right – bottom left.



Article Mode: the screen will be divided into four subpages and the reading order is upper left – bottom left – upper right – bottom right.



More settings


Manually adjust the settings of area cropping, page split, and subpage order.

Crop: Manually select the cropping area for single or double pages.



Split: Split the pages into specified subpages in different ways.

Order: Decide the initial position and reading order for subpages.



Scribble


Handwriting scribble is on by default. It can be turned on/off on the top menu



bar.

The scribble could be called out by tapping on the bot menu bar Scribble.

The scribble content will be directly saved to the original documents, or exported to PDF.





Color

The black and white strokes are shown as their authentic colors. Other colors are shown as black on devices, and the corresponding colors after being exported to PC.



	8 0	≋		Ø •	10 R	1 📙	<u></u>	\leq
广州文石信息科技	支有限公司	(Onyx	Inter	・● 黑色	.) 出品	的 BOC)X 系列	J
阅读产品,凝聚着一	群致力于开	F发新型	型电子	U	家们的	智慧与	心血。	
BOOX 的魅力在于将	强大的功能	与简单	的操作	◎ 绿色	到一起	,为消	费者和	П
内容商提供开放且灵流	舌的电子服务	务平台.		❸ 蓝色				
BOOX 采用 16 级灰度电子纸屏幕,显示效果如同真正的纸张。利用被动式								
采光方式及表面扩散技	支术, 这大力	大减少亿	吏用者	阅读时产生	的眼睛	劳。手	写系统	Ť
让你随时记下阅读笔记	2,并可随时	记录。	灵感。E	BOOX 充分	利用了新	一代电	子纸的	ġ
优点——低耗能,无愿	5光,无背流	七, 😭	姑真	实的阅读感	,极大险	低了纸	张消耗	•
成本,树立环保新理。	8. 同时符	合人们	KIIII	来的阅读习	1惯。			
对于内容提供商。	BOOX 支持	赤格式	定制和	数字版管理	方墓。 又	于各种	主流的	9
电子书和图像格式,我	我们的浏览	器提供	标准化	功能,例如	排版管理	里,字位	本调整	,
全文搜索,内容缩放以	以及页面重	非.						
对于新一代信息平台,网络互联功能非常重要。BOOX的用户可以通过内置						ī		
Copyright © 2019 Onyx International. A	il rights reserved.			/	. 1 .	3 /	65	/65

Sidenote

The sidenote function split pages into two parts in landscape mode, the left side shows the document contents, the right side is blank for note taking. These two sides can be swapped to each other.


The menu is the same as the scribble menu.

The sidenote is only associate with documents instead of pages. The document pages and sidenote page can be turned respectively.



Unlike the scribble, the sidenote will not be embedded to the original documents.

It could be exported manually if needed.



Bottom Menu (after reflow)

Doc, Progress, Format, and Scribble are included. It supports the formats of FPUB\TXT\MOBI\AZW3.

All the functions are available except for the module Format.

Scribble is NOT allowed after reflow.



Only sidenote is supported for note taking. The sidenote is only associate with documents instead of pages. The document pages and sidenote page can be turned respectively.


Format (for font adjustable E-book format)

The settings include Font Face, Display and Spacing.

Load font face in the directory Storage\fronts is supported.

The settings for font size, font face, contrast, bold, spacing work on all newly opened documents, but not work on the documents before settings.







Screenshot


Diagonally tap on two corners of the screen to capture the screen in PNG format.

The function is only available on the reading page.

The screenshot will be saved to the local, or shared by scanning QR code. The save path is \Screenshots.



61 / 136



WeChat and browser scanning are supported for screenshot sharing.

	∠ 返回
Copyright © 2019 Onyx	





Settings

There are Global Settings, touch Settings, TTS Settings, Export Settings, and Version Name for Reading.




☆← 100% 🗐 🤝 🝁 🖰	17:36 🔆 쏍 🐼 🔲
〈 设置	
全局设置	>
触控映射	>
TTS设置	>
导出设置	>
版本号	10711 - f7c8505 (10711)

Global Settings



There are Enable page close reminder, Enable system status bar, Enable reader status bar, Show file borderline, Show virtual buttons in zoom state, Show hyper link.






Touch Settings

Except for the center of the screen, users are able to customize the touch settings for different areas.

There are five default touch models can be chosen and users can customize three more.






TTS Settings

The built-in Baidu TTS is set by default. English is supported. Network connection is required at first use.



Switching to third-party TTS system is allowed. The built-in TTS settings are not synchronized with the system TTS settings. The system TTS settings work on the third-party TTS by default.





Export Settings

The default storage path is Storage\Note.

The export files can be also saved to the same directory as the source file.



	17:43 🌣 伤 🗘 🔲
< 号出设置	
导出到内部存储\Note目录下	✓
导出到与源文件相同目录下	



8. Shop

The Shop is powered by JD.com Inc., offering genuine E-books to purchase. The new users can sign up and login. JD account with purchased E-books is supported. It is currently not available for the synchronization of reading progress and note of JD Reading App.





Login and Sign up

Account and password are required for login and signup. JD or WeChat QR code scanning is also allowed.





After login, you may enter profile by clicking the profile icon on top left.

Personal Books

The list contains the purchased, preview, and VIP borrowed ebooks.

Personal Account

It includes top-up, records of consumption, records of payment, JDReading VIP.

Reading Preference

Based on the reading preference, the system can offer better ebook recommendations for users.

Personal Task

Finish the tasks to earn read beans which can is expense deductible for ebook purchasing.

Gift Center

The shop aperiodically offers gift packages here.












Category

The home page of the Shop contains Ranking, New Book, VIP, Category, Free Book and Sale Book on top. The book information keeps updating aperiodically that users can search the books conveniently.





Book Detail

Click a book cover to open up book detail. The specific book information, price, preview, purchase, abstract, table of content, comments and copyright. All books allow preview for a few chapters. Click "Preview Download" to preview and purchase is available during this reading.





Purchase and Payment

Select books to purchase and add to cart. The E-books can be paid by Read Bean or cash.







VIP Account and VIP Ebook

Users own a VIP account that has some extra rights. VIP E-book is one of the rights that VIP users can borrow for free.

VIP users can read E-books with VIP icon for free until the VIP account is expired.

The VIP E-books can be purchased and it is readable even it is out of stock.






9. Note

Note List

To create new files and folders are allowed.






Drop-down List

It contains Sort by Time (default), Sort by Name, New Folder, Backup and



Restore, and Settings





Folder

Long press on the file icon to pop up the option of moving the files to designated Folder. Multiple layers can be made in the folders.

One file can just be designated to one folder.

The folders are just for better file management. They would be not created in the storage. The note files are readable in storage after being exported.

Backup and Restore

It supports backup and restore for handwritten documents in local or

cloud backup mode.

It supports to delete backup files.

Note: The action Restore will recover the backup data, which will cover the current data. Please be careful.

Settings

This is a general setting for the application Note, including Stylus Calibration, Account Sync and Backup, Show Erasing Trace, etc.

If this device is bound with third-party accounts for file sync, and WIFI is connected, the Note files will be automatically uploaded to the account in PDF attachment.



If auto-connection with Wi-Fi is on for notes sync, the device will connect with Wi-Fi automatically and sync notes to the cloud. When the sync is completed, Wi-Fi will be turned off automatically. (Wi-Fi hotspot should be saved and connected before).




Scribble Interface

Files can be saved automatically and manually when to quit the Note.



Tap on the page number to jump to the specified page quickly.




—→Share

→ Refresh

→ More

Select

In the select mode, circle an area on the screen, then users can zoom, move, duplicate and remove the selected area.



90 / 136






Text Input

Users are allowed to key in words on the note by a Bluetooth keyboard. The input box can be moved everywhere.

Users can adjust the font, line spacing, bolding, underline, italic, copy and delete.






Al Recognition

Click the icon "Al" to switch to recognize the handwriting text. English is supported. To download the corresponding language package is required for other language recognition.

The text flows automatically after reflow. Users can manually make space, newline, and font size after that.

The accuracy of recognition depends on how normal the handwriting is.





Template

It includes built-in templates, local templates and cloud templates.




The directory of the local templates is Storage\note Template.

The directory of the templates downloaded from the cloud is Storage\noteTemplate\cloud.

The built-in templates will be used if the local template are deleted.





Share

Share all pages of a note in PDF format and current page in PNG format.





10. Storage

Storage displays all files from both internal storage.


Files will be displayed in alphabetical order by default. It can be switched to file type, size, create time.

The files can be viewed in thumbnail or list. Multiple selections are allowed.

Users can customize shortcut for folders in storage and place it in the storage interface.

Copyright © 2019 Onyx International. All rights reserved.

The way to make a shortcut: long press the folder > set a shortcut.



11. Apps


All installed Apps are displayed in alphabetical order A-Z by default. Users can choose their preferred order.

Long press on each APP icon to pop up the Apps menu to delete or optimize.

Copyright © 2019 Onyx International. All rights reserved.



Pre-installed applications on devices are not allowed to delete.



Apps Optimization

This is for screen refresh rate. Third party applications can be optimized by several settings includes dpi, contrast, color filter, refresh mode, animation filter, etc. More optimization options will be provided later.



Copyright © 2019 Ony

"Fetch remote optimize config" and "one key to freeze" to the third party apps helps to get a better user experience and save power.






Dictionary


If users use dictionary apps the first time, to download dictionary package to local will be asked.

This function requires network connection.

Word pronunciation needs a dictionary file comes with voice files, currently TTS is not supported.








Users can install dictionaries themselves by putting the dictionary files to designated directory Storage\dicts\.

Please save the files under a folder, e.g.: dicts\English-English Dictionary.






For the preferred dictionary settings, users can select up to 5 preferred



dictionaries. Users will be asked to select again if the select number is less than

1 or more than 5.






After dictionaries are installed, users can look up new words in the search bar. Switch between different dictionaries by tapping a corresponding dictionary title on the bottom.

The search result is in terms of the related dictionary. If the word is unfound, try to use other dictionaries.

Looked-up words can be added to Vocabulary.

Users can divide the Vocabulary into groups. The words will be saved into the specified group once the group is selected.



WiFi Transfer

There is a way to transfer ebooks to the device--WiFi Transfer.

Please ensure that your PC or Android Phone and the device are in the uniform LAN, enter the provided IP address in a browser or scan the provided QR code to accomplish ebook transfer.

During the transfer, do not leave the page until transfer succeed. Supported



formats: TXT, EPUB, PDF, MOBI, JEPG, DOC, PNG.





The ebooks are stored in a default path: \WifiTransfer.

Check the transfer list in "WIFI Transfer History". You may delete the transfer history then the local files in the device would be deleted and vice versa.





App Store (E-ink)

There are some usual third-party apps provided here. These apps are free versions from developers and their compatibility are not verified as full to the system. Paid apps download is not supported for now.

Copyright © 2019 Onyx International. All rights reserved.






Navigation Ball

Navigation Ball is a circular ball that floats above all the apps on the screen. 5 buttons can be customized.



Single click on the ball to expand and collect navigation menu.

It requires to turn off and on again after the new button settings.





The 5 buttons can be set as multiple common functions including system operation, app switching, app optimization and so on.





The app optimization can be called out in an app through the Navigation Ball, for real-time review after optimization (DPI setting requires app restart)



快报 Q 渤海天然气突破

推荐 视频 小视频 生活 热点 娱乐 新时代 精选 〓

一张蓝图一盘棋 习近平这样擘画京津冀协同发展 **TOTAL TOTAL TOTA**

领航新时代 | 吉林:用实干作答以发展求变

置顶 央视网新闻 849 刚刚

世界最"诡异"景点:曾12人进去只有1人出来,却仍有大批游客前往





App Optimization Callout through Navigation Ball

The optimization is the same as the one by long press on app icons.

The settings are synchronized.


448	Q 渤海	天然气突破						
推荐	视频	小视频	生活	热点	娱乐	新时代	精选	≡
		盟棋 习近 □ □ 1660		擘画京	津冀协	同发展		
	领航新时代 吉林:用实干作答以发展求变							
世界最客前往		'景点:管	曾12人這	进去只有	有1人出	来,却仍	3有大批	比游
	-					1		
4					1/2			*
		1	1					r)
	应用			刷新		1	其他	
DPI设置	:(需重启) 300			<u> </u>			+
字体加	1						(
字体颜色	色增强						[✓
图标增强	虽						[
背景颜色	色增强						[✓



12. Settings

It contains product model, Android version, MAC address and firmware version in this page. Users can manage settings of the whole device here and click the device picture for an online user manual.






About Device

Click the model number for more information about the device, including




Capacitive Touch Version, VCom, Other information, Screen Lock Password and Factory Reset.





Screen Lock Password requires 4-8 digital numbers.

Temporarily no password retrieve. Please keep the password and make sure the email address is valid. In the case of losing the password, the device gets a deadlock as our company does not store any private password for users. This device needs to be cleared up and reset by sending back to the factory.





Note: To run the function of factory reset removes all of the user data. Please make a data backup.

Language setting

Users can set system language, TTS reading, dictionary and etc.




Users can set languages of the system and virtue keyboard. The system has an Android keyboard by default. Users can install third-party apps for more input methods.





ONYX Input Method

When using ONYX Input Method for the first time, users need to connect with the Internet to activate it. It could be used for Chinese and English input by default, and users need to download other language packages if they want to input other languages.



Date & Time

Users can choose either auto setting or manual setting for date and time. When the device is connected with the Internet, it will automatically set date and time according to the local time zone. Manual setting requires to set time zone, date and time.

Copyright © 2019 Onyx International. All rights reserved.

Users can select their preferred time and date display format.

Power

Users can set screen auto sleep timeout, power off timeout, network inactivity timeout, etc.

Network

This is for Wi-Fi / VPN / Bluetooth setting.

When Wi-Fi is connected, users can browse webs and download books via the internet on the device.

WiFi Setting

When turning WiFi on, the device will search Wi-Fi hotspots automatically. When all available WLAN are listed, users can choose a network, input password to connect with the internet. WiFi signal will be displayed at "Status

bar" when WiFi is connected.

After WIFI is connected successfully at the first time, the device will save WI-FI information automatically. Users only need to turn on WIFI on notification bar if using the same WIFI next time.

Bluetooth Setting

Turn on Bluetooth, you can search for nearby Bluetooth devices and send connection requests. Bluetooth needs to be paired first.

Currently it only supports the eReader to receive documents, not available to other devices.

VPN Setting

When the VPN is turned on for the first time, the system requires to set a password. This password needs to be used for screen unlock or when the factory settings are restored.

Copyright © 2019 Onyx International, All rights reserved.



Library Setting

Users can choose to scan specified directory in storage, the default scanned files are Books, hop, Wifi Transfer and Push.

When clicking the "Scan whole storage" would scan all the files including system or app log, which may slow down the library loading speed.

Users could set the title display mode through checking the option of "show books' titles instead of their names in library", and books' names are shown by default

Account management

All accounts related data sync and push can be managed here, not including the third-party accounts.





Application

Users can manage the Application setting here, such as installing unknown source Apks, USB debugging, enabling shop, auto freezing newly install applications, enabling Google Play, etc.



The Google Play needs to be activated for the first time. Users need to click the "Enable Google Play" and then click the GSF ID. Next users could register an account with the directions. Last users could log in again 5 to 8 minutes after registration. Users shall reboot the device and log in again if it fails.



Firmware Update

Users can get the Model number, Android version, Build number, and Automatic

Copyright © 2019 Onyx International. All rights reserved.

detection upgrade here. When choosing Check Update, it will check the local package first then online package with a network connection. Upgrade pause and breakpoint download are allowed.

Users should choose update manually since not automatically updating is set by default. Please ensure that the device has more than 15% power and sufficient capacity before the update.

Feedback

Welcome to submit any technical problem or advice to us.

This function collects system information only for problem judgment. And Onyx shall never disclose users' device information.



13. FAQ

How to install a dictionary

The device supports dictionary formats of stardict\bgl\mdict. Users can download the dictionary packages online, and then copy to folder "Root Directory\dicts\". Dictionary is available to use after that.

How to add fonts

Users can download fonts online, then copy the fonts to the folder "Storage\Fonts", which could be created by yourself. Users can select the installed fonts when reading.

How to update

Update locally

Download firmware update.upx from our official website. Copy the firmware to root directory of local storage. Go to Settings –Firmware Update, click the button "Check update", and follow the instructions to update the device.

Update by OTA

Users can update the firmware online via OTA (Setting\Firmware Update). Please connect WiFi and search for the update.upx.

Copyright © 2019 Onyx International. All rights reserved.



How to change screen saver

Press PNG format images to pop up menu, and then click the "Set as screen saver" button.

14. Specifications

	Nova	Nova Pro	
Processor	Quad-core 1.6G Hz		
RAM	2G		
os	Android 6.0		
Storage	32G		
Screen	E-ink display with Regal refresh		



Screen Size	7.8-inch carta screen			
Resolution	1404*1872			
Touch	Capacitive touch	Capacitive touch &		
		electromagnetic touch		
Front Light	Front Light with CTM, adjustable and closeable			
Wireless	WIFI + Bluetooth			
Battery	2800 mAh			
USB	Type-C			
Size	197.3x137x7.7mm			
Weight	≤240 g (battery included)			
Operating	0°C- 50°C			
Temperature				
Book Formats	PDF, EPUB, TXT, DJVU, HTML, FB2, DOC, MOBI, CHM, etc.			
Image Formats	PNG, JPG, BMP			
Audio Formats	WAV, MP3			
Apps	Third party APPs installation is supported			
Browser	Support			

Language	Multi-language supported	
File Directory	Support	
Dictionary	Support	
TTS	Support	
Refreshment A2 quickly refresh, partly refresh and fully refresh		
Mode		
DRM	Support	
Firmware	irmware Locally update and OTA update are available	
Update		
Certification	CE, Rohs	

15. Declaration

Onyx International Inc. reserves the right to modify the content of the Quick Start Guide and User Manual without further notice.

For more information, please visit our website at www.boox.com.